

ICEM 1-150

Measurement service for IC Emission using 1 Ohm/150 Ohm method acc. to IEC 61967-4

LANGER
EMV-Technik

Short description

The ICEM 1-150 measurement service determines the conducted electromagnetic emission (EME) of a test IC by directly measuring the radio frequency (RF) current with a 1 Ω probe and measuring the RF voltage with a 150 Ω coupling network acc. to IEC 61967-4 standard.

Frequency range: 150 kHz – 3 GHz